Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of the Claims:

Claim 1 (currently amended): A method of performing additive synthesis of digital audio signals in a recursive digital oscillator, comprising:

receiving digital audio signal frames wherein each digital audio signal frame includes a set of frequency, amplitude, and phase components represented as coefficients of variables in a mathematical expression, each digital audio signal frame thereby including a frequency coefficient representation;

forming converted frequency coefficients by Re-Mapping ~~linearaly re-mapping~~ of bits of said frequency coefficient representation to bias audio reproduction accuracy toward low frequency signals; and

performing additive synthesis with said converted frequency coefficients.

Claim 2 (original): The method of claim 1 further comprising the step of defining said frequency coefficient representation with an exponent characterizing a floating-point range extension.

Claim 3 (currently amended): The method of claim 2 wherein said defining step includes the step of specifying said exponent to correspond to a right shift amount necessary to

correct for precision limitations introduced by limiting Re-Mapping ~~re-mapping~~ coefficients to 16 bits.

Claim 4 (original): The method of claim 3 wherein said receiving, forming, and performing steps are implemented utilizing a 16-bit fixed point processor.

Claim 5 (original): The method of claim 1 wherein said receiving, forming and performing steps are implemented utilizing a digital signal processor.

Claim 6 (original): The method of claim 1 wherein said receiving, forming, and performing steps are implemented utilizing a field programmable gate array.

Claim 7 (original): The method of claim 1 wherein said receiving, forming, and performing steps are implemented utilizing a Very Long Instruction Word processor.

Claim 8 (original): The method of claim 1 wherein said receiving, forming, and performing steps are implemented utilizing a Reduced Instruction Set Computer.

Claim 9 (original): The method of claim 1 wherein said receiving, forming, and performing steps are implemented utilizing a Residue Number System processor.

Claim 10 (currently amended): A computer readable memory to direct a processor to function in a specified manner, comprising:

a first set of executable instructions to receive digital audio signal frames wherein each digital audio signal frame has a set of specified frequency values expressed as a bit sequence;

a second set of executable instructions to Re-Map ~~transform~~ said bit sequence to represent lower frequencies with more significant bits and higher frequencies with less significant bits; and

a third set of executable instructions to facilitate additive synthesis of said digital audio signal frames in a reduced-precision recursive digital oscillator.

Claim 11 (original): The computer readable memory of claim 10 wherein said first set of executable instructions include instructions to identify a frequency coefficient representation of said specified frequency.

Claim 12 (original): The computer readable memory of claim 11 further comprising a fourth set of executable instructions to define said frequency coefficient representation with an exponent characterizing a floating-point range extension.

Claim 13 (currently amended): The computer readable memory of claim 12 wherein said fourth set of executable instructions include instructions to specify said exponent to correspond to a right shift amount necessary to correct for precision limitations introduced by a reduced ~~reduce~~ precision processor.

Claim 14 (new): A method of performing additive synthesis of digital audio signals comprising:

a) receiving a sequence of digital audio signal frames wherein each digital audio signal frame of said sequence includes a set of frequency, amplitude, and phase components; and,

b) linearly scaling said amplitude component within each of said frames, frame N, wherein N labels a frame of said sequence, from zero to a peak value for a first portion of said frame N, and from said peak value to zero for a second portion of said frame N, creating thereby a scaled frame partial for frame N; and,

c) summing successive scaled frame partials in a overlapping pairwise manner to produce a sequence of summed partials [N, (N+1)], [(N+1), (N+2)], [(N+2), (N+3)] continuing through at least a portion of said sequence, thereby approximating a varying-frequency varying-amplitude frame partial with a sum of two fixed-frequency fixed-amplitude scaled frame partials.

Claim 15 (new): A method as in claim 14 wherein said overlapping pairwise summation comprises approximately 50% overlap between members of each pair of said summed partials.

Claim 16 (new): A recursive digital oscillator generating frequency f lying in the range from zero to one-half of a sampling frequency f_s comprising:

recursion coefficients x_n given by

$x_n = x_{n-1} - \epsilon x_{n-1} - x_{n-2}$

wherein $\epsilon = 2 - 2\cos(\omega)$ and

wherein $\omega = 2\pi f/f_s$.

Claim 17 (new): An oscillator as in claim 16 wherein ε is represented by an unsigned mantissa, m, combined with an unsigned exponent, e, biased so that the actual represented value is

$$\varepsilon = 2^{2-e} m.$$

Claim 18 (new): An oscillator as in claim 17 wherein said mantissa m is 16 bits.